

! CAUTION

- All wiring should be done by a licensed electrician in accordance with state codes, local codes, and National Electrical Code (NEC) or International Electric Commission (IEC) standards.
- Improper installation may result in serious injury and void warranty.
- Contains parts and assemblies susceptible to damage by electrostatic discharge (ESD).
- Surge protective devices should be utilized for fixtures installed in environments subject to power surges outside the specified operating parameters.

Tools and Materials

(1) #3 Phillips head screw driver


Installation

For Highland and Meridian 500 Series fixtures, the glare guard kit comes with two (2) guards for each side of the fixture. Each guard is installed using three (3) machine screws (8-32 x 0.5 inch).

Glare Guard

1. For each side, position glare guard on luminaire as shown (Figure 1).
2. Adjust height of glare guard accordingly to restrict light trespass as needed.
3. Attach glare guard using three (3) machine screws (8-32 x .05 inch) and torque screws to 20 in-lbs.

Figure 1



Product design and specifications are subject to change without notice.

