! CAUTION

- All wiring should be done by a licensed electrician in accordance with state codes, local codes, and National Electric Code (NEC) standards or International Electrotechnical Commission (IEC) standards.
- Improper installation may result in serious injury and void warranty.
- Contains parts and assemblies susceptible to damage by electrostatic discharge (ESD).
- Make sure the fixture is disconnected from any power source before removing from the wall.

Tools and Materials

Phoenix Provided

(1) LED module

(2) small wire crimps

(3) pin-in hex head screws (locking hex head screw)

(3) washers

(1) pin-in hex screwdriver bit

Customer Provided

(1) interchangeable bit screwdriver or drill

(1) wire cutter

(1) wire stripper

(1) crimp tool

(1) 1⁄16 inch hex wrench

Replacement Instructions

1. Remove the three (3) pin-in hex head screws from the LED module face plate using pin-in hex screwdriver head and interchangeable bit screwdriver or drill.
2. Carefully pull the LED module out of the fixture head. Cut the black and white leads above the crimps to disconnect the old module.
3. Pull the black cone-shaped sleeve away from the base of the yellow plastic fixture head to expose the metal ring on the end of the flex arm. Using the 1⁄16 inch hex wrench, loosen the set screw in the ring. Unscrew the yellow head from the metal ring.
4. Thread the leads from the new LED module through the fixture head and out the hole at the base.
5. Remove old crimp and strip the end of each lead. Trim to appropriate length for the small crimps and crimp together like-colored leads.
6. Carefully push the crimps and wire slack back into the head of the fixture. Reattach the head to the metal ring on the flex arm and tighten down the set screw. Slide the black sleeve back into place.
7. Attach the new LED module face plate to the front of the fixture head with three (3) pin-in hex screws and washers. Replace any stripped or damaged screws and washers with ones from the materials Phoenix provided.

Product design and specifications are subject to change without notice.

Phoenix Products Company Inc. 8711 West Port Avenue Milwaukee, WI 53224 USA
Phone: +1 414.973.3300 Toll Free: 800.438.1214 Fax: +1 414.973.3210 **www.phoenixlighting.com**