! CAUTION

- All wiring should be done by a licensed electrician in accordance with state codes, local codes, and National Electric Code (NEC) standards or International Electrotechnical Commission (IEC) standards.
- Improper installation may result in serious injury and void warranty.
- Contains parts and assemblies susceptible to damage by electrostatic discharge (ESD).
- Make sure the fixture is disconnected from any power source before removing from the wall.

Tools and Materials

Phoenix Provided

(1) driver

(5) crimp connectors

(1) driver bracket

Customer Provided

(1) socket wrench for ⅜ inch bolt

(1) socket wrench for 6-32 inch nut

(1) Phillips screwdriver

(1) wire cutter

(1) wire stripper

(1) crimp tool

Replacement Instructions

1. Remove fixture from the wall using the socket wrench for ⅜ inch bolts.
2. Remove three screws from the driver compartment cover using the Phillips screwdriver and remove cover (Figure 1).
3. Using the wire cutter, cut all four wires coming out of the driver box at connection points.
4. Remove the old driver (Figure 2, Item 1).
5. Using the wire stripper, strip the ends of the four wires from the fixture and the four wires off of the new driver.
6. Using supplied driver and driver bracket, mount to the driver compartment cover.
7. Using the crimp tool and crimp connectors supplied, connect each set of wires (Figure 3, Item 2) at the same points where the old connectors were removed. Use the wiring schematic (Figure 3) for proper wire termination.
8. Using the Phillips screwdriver, reinstall the driver compartment cover back onto the driver box with the three screws.
9. Mount fixture to wall using the socket wrench for ⅜ inch bolts.

Phoenix Products Company Inc. 8711 West Port Avenue Milwaukee, WI 53224 USA
Phone: +1 414.973.3300 Toll Free: 800.438.1214 Fax: +1 414.973.3210 **www.phoenixlighting.com**

Figure 1

Driver compartment and bracket

Figure 2

Close up of driver compartment cover from Figure 1

Figure 3

Wiring schematic

Product design and specifications are subject to change without notice.